





LEDS C R II 827 W

302 201 820 W

AVAILABLE IN
WHITE 302 201 820 W



[View on website](#)



General info

LOCATION	interior
INSTALLATION	Wall Recessed
CUTOUT SHAPE/SIZE (MM)	round - 51
RECESSED DEPTH (MM)	46
INGRESS PROTECTION	IP40/20 w
WEIGHT (KG)	0.1
ADJUSTABILITY	non adjustable
INFORMATION	EXCL.LED POWER SUPPLY 350mA-DC

Electrical info

CLASS	III
ENERGY CLASS	E

Lightsource info

Lightsource Name	LED
Lightsource	LED cluster 1,2W / CRI>80 / 2700K / 160lm
LED Technics (light source)	160lm // 1,2W // 130lm/W
LED Technics (luminaire)	54lm // 1W // 39lm/W

Requirements

LED POWER SUPPLY 350mA-DC DIM

Options


CONCRETE BOX 195

For detailed installation instructions, please consult the manual: [302_201_XXX_HAND.pdf](#)

FINISH YOUR SPECIFICATION


LED power supplies

#




300 48 350 ED1 LED POWER CONVERTER 48V-DC to 350 mA-DC / 15W DIM1

2->12

☐



300 48 350 ED5 LED POWER CONVERTER 48V-DC to 350 mA-DC / 15W DIM5

2->12

☐



300 48 350 MDL LED POWER CONVERTER 48V-DC to 350 mA-DC / 15W MDL

2->12

☐



300 48 350 WDL LED POWER CONVERTER 48V-DC to 350 mA-DC / 15W WDL

2->12

☐



300 90 61 LED POWER SUPPLY MULTI-POWER DIM6

13

☐



300 90 63 LED POWER SUPPLY MULTI-POWER DIM9

21(20)

☐



300 90 64 LED POWER SUPPLY MULTI-POWER DIM7

3->15(12)

☐


300 90 67 LED POWER CONVERTER 24V-DC TO MULTI CURRENT 48W DIM9

2->12

☐



300 90 68 LED POWER SUPPLY MULTI-POWER DIM5

2->13(12)

☐

LEDS C R II 827 W


302 201 820 W



300 90 69

LED POWER SUPPLY MULTI-POWER HV DIM9


6->32(32)

☐


300 90 91

LED POWER SUPPLY 350mA-DC / 15W


11(8)

☐


300 90 108

LED POWER SUPPLY 350mA-DC / 8W


6(6)

☐


300 90 110

LED POWER SUPPLY 350mA-DC / 10W DIM8


4->8

☐


300 90 116

LED POWER SUPPLY 350mA-DC / 18W DIM8


8->14

☐


300 90 124

LED POWER SUPPLY MULTI-POWER DIM7


5->14(12)

☐


300 90 125

LED POWER SUPPLY MULTI-POWER MINI DIM5


3->14(12)

☐


300 90 134

LED POWER SUPPLY MULTI-POWER HV DIM7


6->32(32)

☐


300 90 135

LED POWER SUPPLY MULTI-POWER HV

13->24

☐


300 90 3112








LED POWER SUPPLY 350mA-DC / 16W DIM8

5->13(13)

☐

LEDS C R II 827 W

302 201 820 W

	21012 004W	LED POWER SUPPLY MULTI-POWER WDL	21(20)	<input type="checkbox"/>
	21012 005W	LED POWER SUPPLY MULTI-POWER COMPACT WDL	15	<input type="checkbox"/>
	21012 0258	LED POWER SUPPLY MULTI POWER 200-350 / 10W DIM8	5->8	<input type="checkbox"/>
	21012 0268	LED POWER SUPPLY MULTI POWER 200-350 / 15W DIM8	8->12	<input type="checkbox"/>
	21012 0298	LED POWER SUPPLY MULTI POWER 250-900 / 20W DIM8	2->12	<input type="checkbox"/>
	21012 0308	LED POWER SUPPLY 350mA / 7,35W DIM8	4->6	<input type="checkbox"/>
	21032 0295	LED POWER CONVERTER 48V-DC to 350 mA-DC / 15W DIM5	2->12	<input type="checkbox"/>

Concrete boxes

	270 11 195	CONCRETE BOX 195		<input type="checkbox"/>
--	-------------------	------------------	--	--------------------------



LEDS C R II 827 W

302 201 820 W

Notes: