



## MILES C1 SMOKE 92750

23927 9230



 [View on website](#)



### General info

<b>LOCATION</b>	indoor
<b>INSTALLATION</b>	Ceiling Suspended
<b>INGRESS PROTECTION</b>	IP20
<b>WEIGHT (KG)</b>	1.8
<b>ADJUSTABILITY</b>	non adjustable
<b>INFORMATION</b>	REFLECTOR WFL-50° INCL.1 x CABLE 2 x 0.75mm <sup>2</sup> 1,6m INCL.1 x CABLE CLAMP BLACK EXCL.LED POWER SUPPLY 350mA-DC

### Electrical info

<b>CLASS</b>	III
<b>DIM TYPE</b>	depending on power supply
<b>ENERGY CLASS</b>	D
<b>CERTIFICATES</b>	CB, EAC, ENEC

### Lightsource info

<b>LIGHTSOURCE NAME</b>	LED
<b>LIGHTSOURCE</b>	LED array 5,8W / CRI>90 (R9: 60) / 2700K / 753lm
<b>TM-30 VALUES</b>	rf: 89 / Rg: 100
<b>SDCM</b>	SDCM1
<b>RISKGROUP</b>	RG1
<b>LM80</b>	L90B10 > 50000
<b>BEAMANGLE</b>	50°
<b>LED TECHNICS (LIGHT SOURCE)</b>	753lm // 5,8W // 129lm/W
<b>LED TECHNICS (LUMINAIRE)</b>	524lm // 6,7W // 79lm/W

### Requirements

LED POWER SUPPLY 350mA-DC DIM  
MILES POWERBOX 350mA DIM8

### Options

CONNECTION TRIMLESS  
CEILING BASE R  
MILES CEILING BASE 3L / 3R

### Accessories

MILES TUBE

# DELTALIGHT

## MILES C1 SMOKE 92750


23927 9230

For detailed installation instructions, please consult the manual : [23927\\_9230\\_HAND.pdf](#)


### FINISH YOUR SPECIFICATION

#### LED power supplies

#### # of Fixtures

 # of fixtures indicates how many devices can be connected (min -> max) to the power supply. The values before and after the '|' correspond respectively with the minimum and maximum driving current. Values between brackets are applicable to 110V.

Min current | Max current




**300 48 350 ED1** LED POWER CONVERTER 48V-DC to 350 mA-DC / 15W DIM1

1

Dimtype: 1-10V

Cutout dimension (mm): 30




**300 48 350 ED5** LED POWER CONVERTER 48V-DC to 350 mA-DC / 15W DIM5

1

Dimtype: DALI

Cutout dimension (mm): 45




**300 48 350 MDL** LED POWER CONVERTER 48V-DC to 350 mA-DC / 15W MDL

1

Dimtype: non-dimmable

Cutout dimension (mm): 30




**300 48 350 WDL** LED POWER CONVERTER 48V-DC to 350 mA-DC / 15W WDL

1

Dimtype: WDL = wireless dimmable

Cutout dimension (mm): 45




**300 90 61** LED POWER SUPPLY MULTI-POWER DIM6

2

Dimtype: mains (phase cut-off) or push button

Cutout dimension (mm): 56




**300 90 63** LED POWER SUPPLY MULTI-POWER DIM9

4(4)

Dimtype: 1-10V or DALI or push button

Cutout dimension (mm): 82



**300 90 64** LED POWER SUPPLY MULTI-POWER DIM7

2(1)


Dimtype: 1-10V or push button

Cutout dimension (mm): 72

# DELTALIGHT

## MILES C1 SMOKE 92750


23927 9230



**300 90 67** LED POWER CONVERTER 24V-DC TO MULTI CURRENT 48W DIM9

2

Dimtype: 1-10V or DALI or push button




**300 90 68** LED POWER SUPPLY MULTI-POWER DIM5

2(2)

Dimtype: DALI

Cutout dimension (mm): 72




**300 90 69** LED POWER SUPPLY MULTI-POWER HV DIM9

2->6(6)

Dimtype: 1-10V or DALI or push button

Cutout dimension (mm): 84



**300 90 124** LED POWER SUPPLY MULTI-POWER DIM7

3(2)

Dimtype: 1-10V or push button

Cutout dimension (mm): 55




**300 90 125** LED POWER SUPPLY MULTI-POWER MINI DIM5

2(2)

Dimtype: DALI

Cutout dimension (mm): 55




**300 90 135** LED POWER SUPPLY MULTI-POWER HV

3->3

Dimtype: non-dimmable

Cutout dimension (mm): 90




**21012 0010** LED POWER SUPPLY MULTI POWER

2

Dimtype: non-dimmable

Cutout dimension (mm): 50




**21012 0021** LED POWER SUPPLY MULTI POWER DIM1

3

Dimtype: 1-10V

Cutout dimension (mm): 54




**21012 0035** LED POWER SUPPLY MULTI POWER DIM5

3

Dimtype: DALI

Cutout dimension (mm): 54



**21012 004W** LED POWER SUPPLY MULTI-POWER WDL

3(3)


Dimtype: WDL = wireless dimmable

Cutout dimension (mm): 84

# DELTALIGHT

## MILES C1 SMOKE 92750

23927 9230




**21012 005W** LED POWER SUPPLY MULTI-POWER COMPACT WDL

3

**Dimtype:** WDL = wireless dimmable

**Cutout dimension (mm):** 54




**21012 0258** LED POWER SUPPLY MULTI POWER 200-350 / 10W DIM8

1

**Dimtype:** mains (phase cut-off)

**Cutout dimension (mm):** 50




**21012 0298** LED POWER SUPPLY MULTI POWER 250-900 / 20W DIM8

2

**Dimtype:** mains (phase cut-off)

**Cutout dimension (mm):** 48




**21012 0480** LED POWER SUPPLY 350mA-DC / 17W IP68

2(2)

**Dimtype:** non-dimmable

**Cutout dimension (mm):** 60



**21032 0295** LED POWER CONVERTER 48V-DC to 350 mA-DC / 15W DIM5

2

**Dimtype:** DALI

**Cutout dimension (mm):** 30


### Power box

### # of Fixtures



# of fixtures indicates how many devices can be connected (min -> max) to the power supply. The values before and after the '|' correspond respectively with the minimum and maximum driving current. Values between brackets are applicable to 110V.

Min current | Max current




**32942 0018 B** MILES POWERBOX 350 mA DIM8 B

1

**Dimtype:** mains (phase cut-off)

### Electric connection parts



**328 10 03** CONNECTION TRIMLESS O.F.A.

**Cutout dimension (mm):** 62 (CONCRETE: 102)


# DELTALIGHT

## MILES CI SMOKE 92750

23927 9230

### Decorative ornaments

---




**23944 0010 B** MILES TUBE B


**23944 0010 M** MILES TUBE M

### Ceiling bases


---



**23943 0010 B** CEILING BASE R B



**23945 0010 B** CEILING BASE 3L B



**23945 0020 B** CEILING BASE 3R B

Notes: