
DELTALIGHT




# NEEDLE 1 TRC OK 92733

**REFERENCE** 25015 9220 BBR

AVAILABLE IN
**BLACK BRONZE** 25015 9220 BBR
**FLEMISH GOLD** 25015 9220 FG




View on website

| General info | |
|---|---|
| **LOCATION** | indoor |
| **INSTALLATION** | Ceiling Surface mounted |
| **INGRESS PROTECTION** | IP20 |
| **WEIGHT (KG)** | 0.2 |
| **ADJUSTABILITY** | 0° to 50° swiveling, 350° rotatable |
| **INFORMATION** | LENS FL-33°<br>EXCL.LED POWER SUPPLY 350-500mA-DC |

| Electrical info | |
|---|---|
| **CLASS** | III |
| **DIM TYPE** | depending on power supply |
| **ENERGY CLASS** | F |
| **CERTIFICATES** | CB, EAC, ENEC, LCA |

| Lightsource info | |
|---|---|
| **LIGHTSOURCE NAME** | LED |
| **LIGHTSOURCE** | LED array 3,9-5,7W / CRI>90 (R9: 56) / 2700K / 385-519lm |
| **TM-30 VALUES** | Rf: 91 / Rg: 99 |
| **SDCM** | SDCM2 |
| **RISKGROUP** | RG2 (threshold 0,6m) |
| **LM80** | L90B10 > 41000 |
| **BEAMANGLE** | 33° |
| **LED TECHNICS (LIGHT SOURCE)** | 519lm // 5,7W // 90lm/W |
| **LED TECHNICS (LUMINAIRE)** | 380lm // 6,6W // 58lm/W |

**Requirements**

CONNECTION TRIMLESS
LED POWER SUPPLY 350 / 500mA-DC DIM

For detailed installation instructions, please consult the manual : **25015_XXXX_HAND.pdf**

DELTALIGHT

# NEEDLE 1 TRC OK 92733

25015 9220 BBR


## FINISH YOUR SPECIFICATION

### LED power supplies

### # of Fixtures

ⓘ # of fixtures indicates how many devices can be connected (min -> max) to the power supply. The values before and after the '|' correspond respectively with the minimum and maximum driving current. Values between brackets are applicable to 110V.


**Min current | Max current**




**300 48 350 ED1** LED POWER CONVERTER 48V-DC to 350 mA-DC / 15W DIM1 — 3 ☐

**Dimtype: 1-10V**


**Cutout dimension (mm): 30**




**300 48 350 ED5** LED POWER CONVERTER 48V-DC to 350 mA-DC / 15W DIM5 — 3 ☐

**Dimtype: DALI**


**Cutout dimension (mm): 45**




**300 48 350 MDL** LED POWER CONVERTER 48V-DC to 350 mA-DC / 15W MDL — 3 ☐

**Dimtype: non-dimmable**


**Cutout dimension (mm): 30**




**300 48 350 WDL** LED POWER CONVERTER 48V-DC to 350 mA-DC / 15W WDL — 3 ☐

**Dimtype: WDL = wireless dimmable**


**Cutout dimension (mm): 45**




**300 48 500 ED1** LED POWER CONVERTER 48V-DC to 500 mA-DC / 22W DIM1 — 3 ☐

**Dimtype: 1-10V**


**Cutout dimension (mm): 30**




**300 48 500 ED5** LED POWER CONVERTER 48V-DC to 500 mA-DC / 22W DIM5 — 3 ☐

**Dimtype: DALI**


**Cutout dimension (mm): 45**




**300 48 500 MDL** LED POWER CONVERTER 48V-DC to 500 mA-DC / 22W MDL — 3 ☐

**Dimtype: non-dimmable**

**Cutout dimension (mm): 30**





**300 48 500 WDL** LED POWER CONVERTER 48V-DC to 500 mA-DC / 22W WDL — 3 ☐

**Dimtype: WDL = wireless dimmable**

**Cutout dimension (mm): 45**

# NEEDLE 1 TRC OK 92733


25015 9220 BBR




**300 90 61** LED POWER SUPPLY MULTI-POWER DIM6 — 3 | 3

**Dimtype: mains (phase cut-off) or push button**


**Cutout dimension (mm): 56**




**300 90 63** LED POWER SUPPLY MULTI-POWER DIM9 — 6(6) | 6(6)

**Dimtype: 1-10V or DALI or push button**


**Cutout dimension (mm): 82**




**300 90 64** LED POWER SUPPLY MULTI-POWER DIM7 — 2->4(3) | 4(2)


**Dimtype: 1-10V or push button**

**Cutout dimension (mm): 72**




**300 90 67** LED POWER CONVERTER 24V-DC TO MULTI CURRENT 48W DIM9 — 3


**Dimtype: 1-10V or DALI or push button**




**300 90 68** LED POWER SUPPLY MULTI-POWER DIM5 — 4(3) | 4(2)

**Dimtype: DALI**


**Cutout dimension (mm): 72**




**300 90 69** LED POWER SUPPLY MULTI-POWER HV DIM9 — 2->9(10) | 9(6)

**Dimtype: 1-10V or DALI or push button**


**Cutout dimension (mm): 84**




**300 90 92** LED POWER SUPPLY 500mA-DC / 21W — 3(1)

**Dimtype: non-dimmable**


**Cutout dimension (mm): 48**




**300 90 108** LED POWER SUPPLY 350mA-DC / 8W — 1

**Dimtype: non-dimmable**


**Cutout dimension (mm): 40**




**300 90 116** LED POWER SUPPLY 350mA-DC / 18W DIM8 — 3->4

**Dimtype: mains (phase cut-off)**

**Cutout dimension (mm): 55**




**300 90 119** LED POWER SUPPLY 500mA-DC / 11W DIM8 — 1


**Dimtype: mains (phase cut-off)**

**Cutout dimension (mm): 42**

DELTALIGHT

# NEEDLE 1 TRC OK 92733

25015 9220 BBR




**300 90 121** LED POWER SUPPLY 500mA-DC / 20W DIM8 2->3

**Dimtype: mains (phase cut-off)**


**Cutout dimension (mm): 55**




**300 90 124** LED POWER SUPPLY MULTI-POWER DIM7 2->4(3) | 3(2)

**Dimtype: 1-10V or push button**


**Cutout dimension (mm): 55**




**300 90 125** LED POWER SUPPLY MULTI-POWER MINI DIM5 4(3) | 3(2)

**Dimtype: DALI**


**Cutout dimension (mm): 55**




**300 90 134** LED POWER SUPPLY MULTI-POWER HV DIM7 2->8(8) | 8(6) | -

**Dimtype: 1-10V or push button**


**Cutout dimension (mm): 84**




**300 90 135** LED POWER SUPPLY MULTI-POWER HV 5->7 | 4->7 | 4->6

**Dimtype: non-dimmable**


**Cutout dimension (mm): 90**




**300 90 3112** LED POWER SUPPLY 350mA-DC / 16W DIM8 2->3

**Dimtype: mains (phase cut-off)**


**Cutout dimension (mm): 43**




**300 90 5120** LED POWER SUPPLY 500mA-DC / 22W DIM8 3->3

**Dimtype: mains (phase cut-off)**


**Cutout dimension (mm): 61**




**21012 0010** LED POWER SUPPLY MULTI POWER 2->3 | 3

**Dimtype: non-dimmable**


**Cutout dimension (mm): 50**




**21012 0021** LED POWER SUPPLY MULTI POWER DIM1 4 | 4

**Dimtype: 1-10V**

**Cutout dimension (mm): 54**





**21012 0035** LED POWER SUPPLY MULTI POWER DIM5 4 | 4

**Dimtype: DALI**

**Cutout dimension (mm): 54**

# NEEDLE 1 TRC OK 92733


25015 9220 BBR




**21012 004W** LED POWER SUPPLY MULTI-POWER WDL 6(6) | 5(5)

**Dimtype: WDL = wireless dimmable**


**Cutout dimension (mm): 84**




**21012 005W** LED POWER SUPPLY MULTI-POWER COMPACT WDL 4 | 4 | 4

**Dimtype: WDL = wireless dimmable**


**Cutout dimension (mm): 54**




**21012 0258** LED POWER SUPPLY MULTI POWER 200-350 / 10W DIM8 2->2

**Dimtype: mains (phase cut-off)**


**Cutout dimension (mm): 50**




**21012 0268** LED POWER SUPPLY MULTI POWER 200-350 / 15W DIM8 3->3

**Dimtype: mains (phase cut-off)**


**Cutout dimension (mm): 50**




**21012 0278** LED POWER SUPPLY MULTI POWER 500-700 / 20W DIM8 2->2

**Dimtype: mains (phase cut-off)**


**Cutout dimension (mm): 55**




**21012 0288** LED POWER SUPPLY MULTI POWER 500-700 / 36W DIM8 4->4

**Dimtype: mains (phase cut-off)**


**Cutout dimension (mm): 55**




**21012 0298** LED POWER SUPPLY MULTI POWER 250-900 / 20W DIM8 3 | 3 | 3

**Dimtype: mains (phase cut-off)**


**Cutout dimension (mm): 48**




**21012 0480** LED POWER SUPPLY 350mA-DC / 17W IP68 4(3)

**Dimtype: non-dimmable**


**Cutout dimension (mm): 60**




**21012 0500** LED POWER SUPPLY 500mA-DC / 24W IP68 4(2)

**Dimtype: non-dimmable**

**Cutout dimension (mm): 60**




**21032 0295** LED POWER CONVERTER 48V-DC to 350 mA-DC / 15W DIM5 3


**Dimtype: DALI**

**Cutout dimension (mm): 30**

DELTALIGHT

# NEEDLE 1 TRC OK 92733

25015 9220 BBR





**21032 0305** LED POWER CONVERTER 48V-DC to 500 mA-DC / 22W DIM5 — 3

**Dimtype: DALI**

**Cutout dimension (mm): 30**

## Electric connection parts




**328 10 03** CONNECTION TRIMLESS O.F.A.

**Cutout dimension (mm): 62 (CONCRETE: 102)**

Notes: