
DELTALIGHT®




NEEDLE 2 92713 BBR

25012 9210 BBR

AVAILABLE IN
BLACK BRONZE 25012 9210 BBR
FLEMISH GOLD 25012 9210 FG





View on website

General info	
LOCATION	interior
INSTALLATION	Ceiling Surface mounted
INGRESS PROTECTION	IP20
WEIGHT (KG)	0.6
ADJUSTABILITY	non adjustable
INFORMATION	2 x LENS SP-13° EXCL.LED POWER SUPPLY 350-700mA-DC

Electrical info	
CLASS	III
ENERGY CLASS	F

Lightsource info	
Lightsource Name	LED
Lightsource	2 x (LED array 3,9-8,2W / CRI>90 (R9: 56) / 2700K / 385-677lm)
TM-30 Values	Rf: 91 / Rg: 99
SDCM	SDCM2
Riskgroup	RG2 (threshold 0,6m)
LM80	L90B10 > 41000
LED Technics (light source)	1354lm // 16,4W // 83lm/W
LED Technics (luminaire)	950lm // 19W // 50lm/W

Requirements

LED POWER SUPPLY 350 / 500 / 700mA-DC DIM










For detailed installation instructions, please consult the manual: **25012_XXXX_HAND.pdf**

DELTALIGHT®

NEEDLE 2 92713 BBR

25012 9210 BBR











FINISH YOUR SPECIFICATION

LED power supplies		#	
	**300 48 350 ED1**	LED POWER CONVERTER 48V-DC to 350 mA-DC / 15W DIM1	1 ☐
	**300 48 350 ED5**	LED POWER CONVERTER 48V-DC to 350 mA-DC / 15W DIM5	1 ☐
	**300 48 350 MDL**	LED POWER CONVERTER 48V-DC to 350 mA-DC / 15W MDL	1 ☐
	**300 48 350 WDL**	LED POWER CONVERTER 48V-DC to 350 mA-DC / 15W WDL	1 ☐
	**300 48 500 ED1**	LED POWER CONVERTER 48V-DC to 500 mA-DC / 22W DIM1	1 ☐
	**300 48 500 ED5**	LED POWER CONVERTER 48V-DC to 500 mA-DC / 22W DIM5	1 ☐
	**300 48 500 MDL**	LED POWER CONVERTER 48V-DC to 500 mA-DC / 22W MDL	1 ☐
	**300 48 500 WDL**	LED POWER CONVERTER 48V-DC to 500 mA-DC / 22W WDL	1 ☐
	**300 48 700 ED1**	LED POWER CONVERTER 48V-DC to 700 mA-DC / 25W DIM1	1 ☐

DELTALIGHT®

NEEDLE 2 92713 BBR











25012 9210 BBR

	**300 48 700 ED5**	LED POWER CONVERTER 48V-DC to 700 mA-DC / 25W DIM5	1	☐
	**300 48 700 MDL**	LED POWER CONVERTER 48V-DC to 700 mA-DC / 25W MDL	1	☐
	**300 48 700 WDL**	LED POWER CONVERTER 48V-DC to 700 mA-DC / 25W WDL	1	☐
	**300 90 61**	LED POWER SUPPLY MULTI-POWER DIM6	1 / 1 /1	☐
	**300 90 63**	LED POWER SUPPLY MULTI-POWER DIM9	1->3(3) / 1->2(2) / 1->2(2)	☐
	**300 90 64**	LED POWER SUPPLY MULTI-POWER DIM7	1->2(1) / 1->2(1) / 1(0)	☐
	**300 90 67**	LED POWER CONVERTER 24V-DC TO MULTI CURRENT 48W DIM9	1 / 1	☐
	**300 90 68**	LED POWER SUPPLY MULTI-POWER DIM5	1->2(1) / 1->2(1) / 1(1) / 1(0)	☐
	**300 90 69**	LED POWER SUPPLY MULTI-POWER HV DIM9	2->4(4) / 1->4(3) / 1->3(2)	☐
	**300 90 124**	LED POWER SUPPLY MULTI-POWER DIM7	1->2(1) / 1(1) / 1(1) / 1(1)	☐

DELTALIGHT®

NEEDLE 2 92713 BBR






25012 9210 BBR

	**300 90 125**	LED POWER SUPPLY MULTI-POWER MINI DIM5	1->2(1) / 1(1) / 1(1) / 1(1)	☐
	**300 90 135**	LED POWER SUPPLY MULTI-POWER HV	3->3 / 2->3 / 2->3 / 2->3	☐
	**21012 0010**	LED POWER SUPPLY MULTI POWER	1 / 1 / 1	☐
	**21012 0021**	LED POWER SUPPLY MULTI POWER DIM1	1->2 / 1->2 / 1->2	☐
	**21012 0035**	LED POWER SUPPLY MULTI POWER DIM5	1->2 / 1->2 / 1->2	☐
	**21012 004W**	LED POWER SUPPLY MULTI-POWER WDL	1->3(3) / 1->2(2) / 1->2(2)	☐
	**21012 005W**	LED POWER SUPPLY MULTI-POWER COMPACT WDL	1->2 / 1->2 / 1->2 / 1->2	☐
	**21012 0258**	LED POWER SUPPLY MULTI POWER 200-350 / 10W DIM8	1	☐
	**21012 0268**	LED POWER SUPPLY MULTI POWER 200-350 / 15W DIM8	1	☐
	**21012 0278**	LED POWER SUPPLY MULTI POWER 500-700 / 20W DIM8	1 / 1	☐

DELTALIGHT®

NEEDLE 2 92713 BBR

25012 9210 BBR

	**21012 0288**	LED POWER SUPPLY MULTI POWER 500-700 / 36W DIM8	2->2 / 2->2	☐
	**21012 0298**	LED POWER SUPPLY MULTI POWER 250-900 / 20W DIM8	1 / 1 / 1 / 1	☐
	**21032 0295**	LED POWER CONVERTER 48V-DC to 350 mA-DC / 15W DIM5	1	☐
	**21032 0305**	LED POWER CONVERTER 48V-DC to 500 mA-DC / 22W DIM5	1	☐
	**21032 0315**	LED POWER CONVERTER 48V-DC to 700 mA-DC / 25W DIM5	1	☐

Notes: