





NEEDLE 2 OK 92713 FG

25013 9210 FG

AVAILABLE IN

BLACK BRONZE 25013 9210 BBR

FLEMISH GOLD 25013 9210 FG



[View on website](#)



General info

LOCATION	interior
INSTALLATION	Ceiling Surface mounted
INGRESS PROTECTION	IP20
WEIGHT (KG)	0.6
ADJUSTABILITY	0° to 50° swiveling, 350° rotatable
INFORMATION	2 x LENS SP-13° EXCL LED POWER SUPPLY 350-500mA-DC

Electrical info

CLASS	III
ENERGY CLASS	F

Lightsource info

Lightsource Name	LED
Lightsource	2 x (LED array 3,9-5,7W / CRI>90 (R9: 56) / 2700K / 385-519lm)
TM-30 Values	Rf: 91 / Rg: 99
SDCM	SDCM2
Riskgroup	RG2 (threshold 0,6m)
LM80	L90B10 > 41000
LED Technics (light source)	1038lm // 11,4W // 90lm/W
LED Technics (luminaire)	728lm // 13W // 56lm/W










Requirements

LED POWER SUPPLY 350 / 500mA-DC DIM











For detailed installation instructions, please consult the manual: [25013_XXXX_HAND.pdf](#)

NEEDLE 2 OK 92713 FG
25013 9210 FG

FINISH YOUR SPECIFICATION


LED power supplies		#
	300 48 350 ED1 LED POWER CONVERTER 48V-DC to 350 mA-DC / 15W DIM1	1 <input type="checkbox"/>
	300 48 350 ED5 LED POWER CONVERTER 48V-DC to 350 mA-DC / 15W DIM5	1 <input type="checkbox"/>
	300 48 350 MDL LED POWER CONVERTER 48V-DC to 350 mA-DC / 15W MDL	1 <input type="checkbox"/>
	300 48 350 WDL LED POWER CONVERTER 48V-DC to 350 mA-DC / 15W WDL	1 <input type="checkbox"/>
	300 48 500 ED1 LED POWER CONVERTER 48V-DC to 500 mA-DC / 22W DIM1	1 <input type="checkbox"/>
	300 48 500 ED5 LED POWER CONVERTER 48V-DC to 500 mA-DC / 22W DIM5	1 <input type="checkbox"/>
	300 48 500 MDL LED POWER CONVERTER 48V-DC to 500 mA-DC / 22W MDL	1 <input type="checkbox"/>
	300 48 500 WDL LED POWER CONVERTER 48V-DC to 500 mA-DC / 22W WDL	1 <input type="checkbox"/>
	300 90 61 LED POWER SUPPLY MULTI-POWER DIM6	1/1 <input type="checkbox"/>

NEEDLE 2 OK 92713 FG
25013 9210 FG

	300 90 63	LED POWER SUPPLY MULTI-POWER DIM9	1->3(3) / 1->2(2) <input type="checkbox"/>
	300 90 64	LED POWER SUPPLY MULTI-POWER DIM7	1->2(1) / 1->2(1) <input type="checkbox"/>
	300 90 67	LED POWER CONVERTER 24V-DC TO MULTI CURRENT 48W DIM9	1/1 <input type="checkbox"/>
	300 90 68	LED POWER SUPPLY MULTI-POWER DIM5	1->2(1) / 1->2(1) / 1(1) <input type="checkbox"/>
	300 90 69	LED POWER SUPPLY MULTI-POWER HV DIM9	2->4(4) / 1->4(3) <input type="checkbox"/>
	300 90 124	LED POWER SUPPLY MULTI-POWER DIM7	1->2(1) / 1(1) / 1(1) <input type="checkbox"/>
	300 90 125	LED POWER SUPPLY MULTI-POWER MINI DIM5	1->2(1) / 1(1) / 1(1) <input type="checkbox"/>
	300 90 135	LED POWER SUPPLY MULTI-POWER HV	3->3 / 2->3 / 2->3 <input type="checkbox"/>
	21012 0010	LED POWER SUPPLY MULTI POWER	1/1 <input type="checkbox"/>
	21012 0021	LED POWER SUPPLY MULTI POWER DIM1	1->2 / 1->2 <input type="checkbox"/>

NEEDLE 2 OK 92713 FG


25013 9210 FG



21012 0035

LED POWER SUPPLY MULTI POWER DIM5


1->2 / 1->2

☐


21012 004W

LED POWER SUPPLY MULTI-POWER WDL


1->3(3) / 1->2(2)

☐


21012 005W

LED POWER SUPPLY MULTI-POWER COMPACT WDL


1->2 / 1->2 / 1->2

☐


21012 0258

LED POWER SUPPLY MULTI POWER 200-350 / 10W DIM8


1

☐


21012 0268

LED POWER SUPPLY MULTI POWER 200-350 / 15W DIM8


1

☐


21012 0278

LED POWER SUPPLY MULTI POWER 500-700 / 20W DIM8


1/1

☐


21012 0288

LED POWER SUPPLY MULTI POWER 500-700 / 36W DIM8


2->2 / 2->2

☐


21012 0298

LED POWER SUPPLY MULTI POWER 250-900 / 20W DIM8


1/1/1

☐


21032 0295

LED POWER CONVERTER 48V-DC to 350 mA-DC / 15W DIM5

1

☐


21032 0305

LED POWER CONVERTER 48V-DC to 500 mA-DC / 22W DIM5

1

☐



NEEDLE 2 OK 92713 FG

25013 9210 FG

Notes: