





NEEDLE 1 92733 FG

25010 9220 FG

AVAILABLE IN
BLACK BRONZE 25010 9220 BBR
FLEMISH GOLD 25010 9220 FG



[View on website](#)

General info

LOCATION	indoor
INSTALLATION	Ceiling Surface mounted
INGRESS PROTECTION	IP20
WEIGHT (KG)	0.3
ADJUSTABILITY	non adjustable
INFORMATION	LENS FL-33° EXCL.LED POWER SUPPLY 350-700mA-DC

Electrical info

CLASS	III
DIM TYPE	depending on type of external power supply
ENERGY CLASS	F
CERTIFICATES	CB, EAC, ENEC

Lightsource info

LIGHTSOURCE NAME	LED
LIGHTSOURCE	LED array 3,9-8,2W / CRI>90 (R9: 56) / 2700K / 385-677lm
TM-30 VALUES	Rf: 91 / Rg: 99
SDCM	SDCM2
RISKGROUP	RG2 (threshold 0,6m)
LM80	L90B10 > 41000
LED TECHNICS (LIGHT SOURCE)	677lm // 8,2W // 83lm/W
LED TECHNICS (LUMINAIRE)	496lm // 9W // 53lm/W

Requirements










LED POWER SUPPLY 350 / 500 / 700mA-DC DIM

For detailed installation instructions, please consult the manual: [25010_XXXX_HAND.pdf](#)

NEEDLE 1 92733 FG


25010 9220 FG

FINISH YOUR SPECIFICATION

LED power supplies			#
	300 90 63 LED POWER SUPPLY MULTI-POWER DIM9	1->6(6) / 1->5(5) / 1->5(4)	<input type="checkbox"/>
	300 90 68 LED POWER SUPPLY MULTI-POWER DIM5	1->4(3) / 1->4(2) / 1->3(2) / 1->3(1)	<input type="checkbox"/>
	300 90 69 LED POWER SUPPLY MULTI-POWER HV DIM9	3->9(9) / 1->9(6) / 1->6(4)	<input type="checkbox"/>
	300 90 124 LED POWER SUPPLY MULTI-POWER DIM7	2->4(3) / 1->3(2) / 1->3(2) / 1->2(1)	<input type="checkbox"/>
	300 90 125 LED POWER SUPPLY MULTI-POWER MINI DIM5	2->4(3) / 1->3(2) / 1->3(2) / 1->2(1)	<input type="checkbox"/>
	21012 0010 LED POWER SUPPLY MULTI POWER	2->3 / 2->3 / 1->3	<input type="checkbox"/>
	21012 0021 LED POWER SUPPLY MULTI POWER DIM1	2->4 / 2->4 / 1->4	<input type="checkbox"/>
	21012 0035 LED POWER SUPPLY MULTI POWER DIM5	2->4 / 2->4 / 1->4	<input type="checkbox"/>
	21012 005W LED POWER SUPPLY MULTI-POWER COMPACT WDL	1->4 / 1->4 / 1->4 / 1->4	<input type="checkbox"/>


NEEDLE 1 92733 FG

25010 9220 FG




21012 0258 LED POWER SUPPLY MULTI POWER 200-350 / 10W DIM8

2->2 ☐




21012 0268 LED POWER SUPPLY MULTI POWER 200-350 / 15W DIM8

3->3 ☐




21012 0278 LED POWER SUPPLY MULTI POWER 500-700 / 20W DIM8

2->2 / 2->2 ☐




21012 0288 LED POWER SUPPLY MULTI POWER 500-700 / 36W DIM8

4->4 / 3->4 ☐




21012 0298 LED POWER SUPPLY MULTI POWER 250-900 / 20W DIM8

1->3 / 1->3 / 1->3 / 1->2 ☐




21032 0295 LED POWER CONVERTER 48V-DC to 350 mA-DC / 15W DIM5

1->3 ☐



21032 0305 LED POWER CONVERTER 48V-DC to 500 mA-DC / 22W DIM5

1->3 ☐



21032 0315 LED POWER CONVERTER 48V-DC to 700 mA-DC / 25W DIM5

1->3 ☐

Notes: