





NEEDLE 1 TRC OK 93013 BBR

25015 9310 BBR

AVAILABLE IN
BLACK BRONZE 25015 9310 BBR
FLEMISH GOLD 25015 9310 FG



[View on website](#)



General info

LOCATION	indoor
INSTALLATION	Ceiling Surface mounted
INGRESS PROTECTION	IP20
WEIGHT (KG)	0.2
ADJUSTABILITY	0° to 50° swiveling, 350° rotatable
INFORMATION	LENS SP-13° EXCL.LED POWER SUPPLY 350-500mA-DC

Electrical info

CLASS	III
DIM TYPE	depending on type of external power supply
ENERGY CLASS	F
CERTIFICATES	CB, EAC, ENEC

Lightsource info

LIGHTSOURCE NAME	LED
LIGHTSOURCE	LED array 3,9-5,7W / CRI>90 (R9: 55) / 3000K / 385-519lm
TM-30 VALUES	Rf: 92 / Rg: 98
SDCM	SDCM2
RISKGROUPE	RG2 (threshold 0,6m)
LM80	L90B10 > 41000
LED TECHNICS (LIGHT SOURCE)	519lm // 5,7W // 90lm/W
LED TECHNICS (LUMINAIRE)	364lm // 7W // 56lm/W










Requirements

CONNECTION TRIMLESS
LED POWER SUPPLY 350 / 500mA-DC DIM








For detailed installation instructions, please consult the manual: [25015_XXXX_HAND.pdf](#)

NEEDLE 1 TRC OK 93013 BBR
25015 9310 BBR

FINISH YOUR SPECIFICATION

LED power supplies			#
	300 90 63 LED POWER SUPPLY MULTI-POWER DIM9	1->6(6) / 1->5(5)	<input type="checkbox"/>
	300 90 68 LED POWER SUPPLY MULTI-POWER DIM5	1->4(3) / 1->4(2) / 1->3(2)	<input type="checkbox"/>
	300 90 69 LED POWER SUPPLY MULTI-POWER HV DIM9	3->9(9) / 1->9(6)	<input type="checkbox"/>
	300 90 124 LED POWER SUPPLY MULTI-POWER DIM7	2->4(3) / 1->3(2) / 1->3(2)	<input type="checkbox"/>
	300 90 125 LED POWER SUPPLY MULTI-POWER MINI DIM5	2->4(3) / 1->3(2) / 1->3(2)	<input type="checkbox"/>
	21012 0010 LED POWER SUPPLY MULTI POWER	2->3 / 2->3	<input type="checkbox"/>
	21012 0021 LED POWER SUPPLY MULTI POWER DIM1	2->4 / 2->4	<input type="checkbox"/>
	21012 0035 LED POWER SUPPLY MULTI POWER DIM5	2->4 / 2->4	<input type="checkbox"/>
	21012 005W LED POWER SUPPLY MULTI-POWER COMPACT WDL	1->4 / 1->4 / 1->4	<input type="checkbox"/>

NEEDLE 1 TRC OK 93013 BBR
25015 9310 BBR

	21012 0258 LED POWER SUPPLY MULTI POWER 200-350 / 10W DIM8	2->2 <input type="checkbox"/>
	21012 0268 LED POWER SUPPLY MULTI POWER 200-350 / 15W DIM8	3->3 <input type="checkbox"/>
	21012 0278 LED POWER SUPPLY MULTI POWER 500-700 / 20W DIM8	2->2 <input type="checkbox"/>
	21012 0288 LED POWER SUPPLY MULTI POWER 500-700 / 36W DIM8	4->4 <input type="checkbox"/>
	21012 0298 LED POWER SUPPLY MULTI POWER 250-900 / 20W DIM8	1->3 / 1->3 / 1->3 <input type="checkbox"/>
	21032 0295 LED POWER CONVERTER 48V-DC to 350 mA-DC / 15W DIM5	1->3 <input type="checkbox"/>
	21032 0305 LED POWER CONVERTER 48V-DC to 500 mA-DC / 22W DIM5	1->3 <input type="checkbox"/>

Electric connection parts

	328 10 03 CONNECTION TRIMLESS O.F.A.	<input type="checkbox"/>
--	---	--------------------------



NEEDLE 1 TRC OK 93013 BBR

25015 9310 BBR

Notes: