



PARTOU OK 93018 W-W



25214 9310 W-W

AVAILABLE IN

BLACK-BLACK 25214 9310 B-B

BLACK-DARK CHROMED 25214 9310 B-DC

WHITE-WHITE 25214 9310 W-W



[View on website](#)

General info

LOCATION	interior
INSTALLATION	Ceiling Recessed
CUTOUT SHAPE/SIZE (MM)	round - 76
RECESSED DEPTH (MM)	90
THICKNESS OF MOUNTING SURFACE (MM)	min.5
INGRESS PROTECTION	IP20
WEIGHT (KG)	0.2
ADJUSTABILITY	0° to 20° swiveling
INFORMATION	REFLECTOR SP-18° EXCL.LED POWER SUPPLY 350-500mA-DC

Electrical info

CLASS	III
ENERGY CLASS	E

Lightsource info

Lightsource Name	LED
Lightsource	LED array 5,8-8,6W / CRI>90 (R9: 52) / 3000K / 734-1018lm
TM-30 Values	Rf: 90 / Rg: 99
SDCM	SDCM1
Riskgroup	RG1
LM80	L90B10 > 50000
LED Technics (light source)	1018lm // 8,6W // 118lm/W
LED Technics (luminaire)	790lm // 10W // 80lm/W

Requirements

LED POWER SUPPLY 350 / 500mA-DC DIM

Options

PLASTERKIT 101

PARTOU OK 93018 W-W

25214 9310 W-W

For detailed installation instructions, please consult the manual: [25214_XXX0_HAND.pdf](#)

CEILING COMPATIBILITY

Ceiling Type	Mounting Kit
 System ceiling	-
 Plasterboard	-
 Stucanet	-
 Wood	-
 Concrete	-
 Concrete + plaster	 PLASTERKIT 101 Required
 Lintel + plaster	 PLASTERKIT 101 Required
 Hollow-core slab	-
 Hollow-core slab + plaster	 PLASTERKIT 101 Required
 Stretched ceiling	-


PARTOU OK 93018 W-W

25214 9310 W-W

FINISH YOUR SPECIFICATION


LED power supplies

#




300 48 350 ED1 LED POWER CONVERTER 48V-DC to 350 mA-DC / 15W DIM1

1->2

☐



300 48 350 ED5 LED POWER CONVERTER 48V-DC to 350 mA-DC / 15W DIM5

1->2

☐



300 48 350 MDL LED POWER CONVERTER 48V-DC to 350 mA-DC / 15W MDL

1->2

☐



300 48 350 WDL LED POWER CONVERTER 48V-DC to 350 mA-DC / 15W WDL

1->2

☐



300 48 500 ED1 LED POWER CONVERTER 48V-DC to 500 mA-DC / 22W DIM1

1->2

☐



300 48 500 ED5 LED POWER CONVERTER 48V-DC to 500 mA-DC / 22W DIM5

1->2

☐



300 48 500 MDL LED POWER CONVERTER 48V-DC to 500 mA-DC / 22W MDL

1->2

☐


300 48 500 WDL LED POWER CONVERTER 48V-DC to 500 mA-DC / 22W WDL

1->2

☐



300 90 61 LED POWER SUPPLY MULTI-POWER DIM6

1->2 / 1->2

☐

PARTOU OK 93018 W-W


25214 9310 W-W



300 90 63

LED POWER SUPPLY MULTI-POWER DIM9


1->4(4) / 1->4(3)



300 90 64

LED POWER SUPPLY MULTI-POWER DIM7


1->3(2) / 1->2(1)



300 90 67

LED POWER CONVERTER 24V-DC TO MULTI CURRENT 48W DIM9


1->2 / -



300 90 68

LED POWER SUPPLY MULTI-POWER DIM5


1->2(2) / 1->2(1)



300 90 69

LED POWER SUPPLY MULTI-POWER HV DIM9


2->6(6) / 1->6(4)



300 90 91

LED POWER SUPPLY 350mA-DC / 15W


2(1)



300 90 124

LED POWER SUPPLY MULTI-POWER DIM7


1->2(2) / 1->2(1)



300 90 125

LED POWER SUPPLY MULTI-POWER MINI DIM5


1->2(2) / 1->2(1)



300 90 135

LED POWER SUPPLY MULTI-POWER HV

3->4 / 2->4



21012 0010










LED POWER SUPPLY MULTI POWER

1->2 / 1->2




PARTOU OK 93018 W-W

25214 9310 W-W

	21012 0021	LED POWER SUPPLY MULTI POWER DIM1	1->3 / 1->3 ☐
	21012 0035	LED POWER SUPPLY MULTI POWER DIM5	1->3 / 1->3 ☐
	21012 004W	LED POWER SUPPLY MULTI-POWER WDL	1->4(4) / 1->4(3) ☐
	21012 005W	LED POWER SUPPLY MULTI-POWER COMPACT WDL	1->3 / 1->3 ☐
	21012 0258	LED POWER SUPPLY MULTI POWER 200-350 / 10W DIM8	1 ☐
	21012 0268	LED POWER SUPPLY MULTI POWER 200-350 / 15W DIM8	2->2 ☐
	21012 0278	LED POWER SUPPLY MULTI POWER 500-700 / 20W DIM8	1 ☐
	21012 0288	LED POWER SUPPLY MULTI POWER 500-700 / 36W DIM8	2->2 ☐
	21012 0298	LED POWER SUPPLY MULTI POWER 250-900 / 20W DIM8	1->2 / 1->2 ☐
	21012 0308	LED POWER SUPPLY 350mA / 7,35W DIM8	1 ☐

PARTOU OK 93018 W-W


25214 9310 W-W



21012 0318

LED POWER SUPPLY 500mA / 10W DIM8


1



21032 0295

LED POWER CONVERTER 48V-DC to 350 mA-DC / 15W DIM5

1->2




21032 0305

LED POWER CONVERTER 48V-DC to 500 mA-DC / 22W DIM5

1->2



Plasterkits



202 11 19 PLASTERKIT 101



Notes: